

Floor Guard Wi-Fi



Zero False Alarm 58 KHz Acustomagnetic EAS

*Our patented system algorithm avoids false alarms when walking through the system.

Floor Guard Wi-Fi

Invisible System is visibly better

Your store will impress your customer. And with the WG Wi-Fi Floor Guard Hybrid at your entrance nothing interferes with this impression.

Fully invisible with cutting edge technology. Just the way your store was planned and implemented by your architect.

The Wi-Fi Floor Guard antennas disappear completely in the floor an additional loop antenna integrates into a nonmagnetic door frame or wall.

Compared to other Floor EAS Antennas the invisible Wi-Fi Floor Guard Hybrid lifts the detection area and allows the use of smaller tags.



Wi-Fi Floor Guard applications



Wi-Fi Floor Guard is specifically designed for the exclusive Fashion, Outdoor, Sport and the Luggage market. Its best used with our small high-performance ferrite tag Super Pencil (2.3"), the (19")

Pencil tag or the Shell tag (2.1"). Detection performance will be in one level with the best visible retail security systems.

Entrances are protected and completely invisible.



Alarm zone:

| Type of tag | Detection Height |
|-------------------|------------------|
| Shell, Mid Pencil | 3") ft - 4ft |
| Super Pencil | 3.7 ft - 4.75 ft |

* Since the influence of metal in the soil can not be determined reliably in advance, we recommend the use of powerful tags like WG Super Pencil, WG Pencil or WG Shell tags. Underperforming labels will reach lower detection levels. And lower detection height.

To avoid alarms by labels in the close proximity of the antennas, a safety zone with no tags (about 40-45% of the exit width) should be kept on all sides. AM EAS systems are radio transmission systems on the approved working frequency of 58 KHz. Devices being unsuppressed or not corresponding to recent standards (EN 300330 / EN 301489-3) can cause interference and negatively affect system performance. Changes in the environment and surrounding may require a retuning of any EAS System.

Wi-Fi Floor Guard Antenna prior to pouring concrete

Floor Guard Hybrid Wi-Fi Installation Description:



The Wi-Fi Floor Guard Antenna is installed into a recess floor. Due to the 1inch cable diameter its much easier and more feasible than in previous floor antenna systems. The antenna is cast in thin set and can be covered by non metallic floor materials such as brick, wood, carpet, marble etc.

If an entrance-mat is framed by metal this must not form a closed circuit to avoid the effect of a Faraday cage, with negative influences on the signal field. A single cut of 1mm at a hidden position will solve the problem. To any magnetic metal a proximity of about 3 - 4 inches is recommended. The floor antenna is connected through a max. 20ft long system cable to a tuning box.

In the **Adapter box** the raw antenna signals are processed and made resistant against interferences. Therefore the shorter this cable is, the better it is. With the 20ft cable from the floor antenna usually the ceiling can be reached and the box can be located next to the controller. On very wide openings, where the cable length is not sufficient to reach the ceiling, the tuning box may be positioned behind a Revision-door in the wall or in the furniture. The tuning box is connected to the system controller.

The **System controller** processes all transmitter and receiver signals. Usually it is located behind a revision door in the false ceiling or a cabinet. It offers audio-alarm and WiFi connection for remote service. If the alarm volume is too low because the controller is mounted covert, an optional digital remote alarm (audible + optical alarm) unit can be used. Cables between tuning box and controller can be up to 50ft long. The controller is operated by 24 V low volt-age coming from a WG Smart Power Supply.

The ideal position for the Controller, Tuning Box and Power supply is to left or right side of the door. Alternatively a soffit in the ceiling close to the exit can be used.

The SPS has connection joints for dry contacts to trigger a CCTV-system in case of EAS-alarm or jammer-alarm. Also the alarm volume can be adjusted remotely from the SPS. The exclusive TX-switch is a great support for the store people if they search for labels in the security zone. SPS can be clicked on a standard DIN-rail (Din 46277-3) holder system.

Floor Guard Wi-Fi Specifications:



System controller with SPS Smart Power supply on the mounting plate



Floor Guard Adapter Box

Options:



Optional external alarm units can be flush mounted into the store ceiling

Dimensions

| | | |
|------------------------|------------------------|---------|
| Metal Mounting pPlate: | 18 x 13 x 3.3 inches | 1.1 lbs |
| System Controller: | 15 x 5.5 x 2.8 inches | 5.3 lbs |
| SPS Power Supply: | 4.4 x 5.5 x 3.1 inches | 7 lbs |
| Adapter Box: | 9.5 x 7.5 x 3.3 inches | 2.5 lbs |

Floor antenna dimensions:

| | | |
|---------------------|----------------------|--------|
| Floor Antenna WF FG | 60 x 16 x 1.1 inches | 11 lbs |
|---------------------|----------------------|--------|

Max. Cable length:

| | |
|---------------------------------|--------------------------------|
| Antenna / Tuning box: | 20 ft |
| Hybrid Loop Cable to Controller | max 6ft |
| Tuning box / Controller | 50 ft |
| Controller to External SPS | 250 ft with WG EA-Type 2 cable |

Power Preparations:

110 V (min. 3x2.5 mm²) Fuse 16 A min.. on dedicated circuit, at the same phase (L1 recommended) for all systems and deactivators at the cash desks. Current consumption max. 50 W per system, and 10/120 W (continuous / peak-pulse) per deactivator. Terminal connection or untwist able sockets. Plastic conduits (1 inch) with an inserted pull string is required.

External alarm connection- 2 conductor alarm cable or CAT 5/6 cable can be used.

Product Codes:

| | |
|-------------|------------------------------------|
| WG WFFG | Floor Guard antenna* |
| WG WFCB | Floor Guard Controller |
| WG WFFG2A6 | 6ft Floor Guard antenna coil set* |
| WG WFFG2A10 | 10ft Floor Guard antenna coil set* |
| WG WFFG2A12 | 12ft Floor Guard antenna coil set* |

*includes adapter box dedicated for this configuration.



Your Partner in Profit

Floor Guard 2A Wi-Fi



Zero False Alarm* 58 KHz Acustomagnetic EAS

*Our patented system algorithm avoids false alarms when walking through the system.

Floor Guard Wi-Fi

Invisible System is visibly better

Your store will impress your customer. And with the WG Wi-Fi Floor 2A Hybrid at your entrance nothing interferes with this impression.

Fully invisible with cutting edge technology. Just the way your store was planned and implemented by your architect.

The Wi-Fi Floor Guard antennas disappear completely in the floor an additional loop antenna integrates into a nonmagnetic door frame or wall.

Compared to other Floor EAS Antennas the invisible Wi-Fi Floor Guard Hybrid lifts the detection area and allows the use of smaller tags.



Wi-Fi Floor Guard Applications



Wi-Fi Floor Guard is specifically designed for the exclusive Fashion, Outdoor, Sport and the Luggage market. It's best used with our small high-performance ferrite tag "Super Pencil" (2.3"), the (1.9") Pencil tag or the Shell-tag (2.1"). Detection performance will be in one level with the best visible retail security systems.

Entrances are protected and completely invisible.



Alarm Zone:


| Type of tag | Detection Height |
|-------------------|-------------------|
| Shell, Mid Pencil | 3.6 ft - 4.4 ft |
| Super Pencil | 3.77 ft - 4.75 ft |

* Since the influence of metal in the soil can not be determined reliably in advance, we recommend the use of powerful tags like WG Super Pencil, WG Pencil or WG Shell tags. Under performing labels will reach lower detection levels and lower detection height.

To avoid alarms by labels in the close proximity of the antennas, a safety zone with no tags (about 40-45% of the exit width) should be kept on all sides. AM EAS systems are radio transmission systems on the approved working frequency of 58 KHz. Devices being unsuppressed or not corresponding to recent standards (EN 300330 / EN 301489-3) can cause interference and negatively affect system performance. Changes in the environment and surrounding may require a retuning of any EAS System.

Wi-Fi Floor Guard 2A laid on the floor for testing. This is done prior to the antenna channel being cut into the floor.

Floor Guard 2A Wi-Fi Installation Description:



The WiFi **Floor Guard 2A Antenna** is a configurerd antenna cable set,available in three sizes:

WG WFFG2A6 **Wi-Fi Floor Guard "2A"** **6ft antenna floor loops**

WG WFFG2A10 **Wi-Fi Floor Guard "2A"** **10ft antenna floor loops**

WG WFFG2A12 **Wi-Fi Floor Guard "2A"** **12ft antenna floor loops**

Consisting of three loop cables and a dedicated adapter box to connect to a WG Wi-Fi Control Box (WFCB). Other then all other floor antennas that are a solid plate of 2" the 2A antennas do not need a massive hole in the floor. They can either be cut into concrete or laid inside the tile glue or integrated inside the floor construction below wood-en floors. The antenna coils can be covered by non-metallic floor materials such as brick, wood, carpet, marble etc..

If an entrance mat is framed by metal this must not form a closed circuit to avoid the effect of a Faraday cage, with negative influences on the signal field. A single cut of 1mm at a hidden position will solve the problem. To any magnetic metal a proximity of about 3" is recommended. The floor antenna is connected through a max. 20 ft long system cable to a tuning box.

In the **Adapter box** the raw antenna signals are processed and made resistant against interferences. Therefore the shorter this cable is, the better it is. With the 20 ft cable from the antenna usually the ceiling can be reached and the box is located next to the controller. On very wide openings, where the cable length is not sufficient to reach the ceiling, the tuning box may be positioned behind a Revision door in the wall or in the furniture. The tuning box is connected to the system controller.

The **System controller** processes all transmitter and receiver signals. Usually it is located behind a revision door in the false ceiling or a cabinet. It offers audio alarm and WiFi Connection for remote service. If the alarm volume is too low because the controller is mounted covert, an optional digital remote alarm (audible + optical alarm) unit can be used. Cables between tuning box and controller can be up to 50 ft long. The controller is operated by 24 V low voltage coming from a WG Smart Power Supply.

The SPS has connection joints for dry contacts to trigger a CCTV-system in case of EAS alarm or jammer alarm. Also the alarm volume can be adjusted remotely from the SPS. The exclusive TX-switch is a great support for the store people if they search for labels in the security zone. SPS can be clicked on a standard DIN-rail (Din 46277-3) holder system.

Wi-Fi Floor Guard 2A - specifications

Wi-Fi Floor Guard 2A is a special variation of WG's Floor Guard technology, using pre configured transmitter and receiver antenna cable coils that can be cast with liquid concrete, cut into solid concrete or laid inside tile glue. It is available in three dimensions, 6ft, 10ft and 12ft. The width is always 3ft the diameter of the cables below 0.4 inch

Each antenna consists of three coils. A large one, with two small ones inside. Each coil is connected to the dedicated Adapter Box (20ft cable) which first processes the raw antenna signals. The Adapter Box is connected to the Wi-Fi Floor Guard Controller (WFCB) controller with two max 50ft long system cables.



Floor Guard Wi-Fi Specifications:



System controller with SPS-Smart Power supply on the mounting plate



Floor Guard Adapter box

Options:



Optional external alarm units can be flush mounted into the store ceiling.

Dimensions

| | | |
|-----------------------|------------------------|---------|
| Metal Mounting Plate: | 18 x 13 x 3.3 inches | 1.1lbs |
| System Controller: | 15 x 5.5 x 2.5 inches | 5.3 lbs |
| SPS Power Supply: | 4.4 x 5.4 x 3.1 inches | 7 lbs |
| Adapter Box: | 9.5 x 7.5 x 3.5 inches | 2.5 lbs |

Floor antenna dimensions:

| | | |
|-----------------------------|----------------------|----------|
| | 60x 16x 1.1 inches | 11lbs |
| 2A Floor Antenna Coils 6ft | 6 x 3 x 10 inches | 1.1lbs |
| 2A Floor Antenna Coils 10ft | 12 x 3.5 x 10 inches | 4.75 lbs |
| 2A Floor Antenna Coils 12ft | 15 x 3.5 x 4 inches | 5.3 lbs |

Max. Cable length:

| | |
|---------------------------------|--------------------------------|
| Antenna / Tuning Box: | 20ft |
| Hybrid Loop Cable to Controller | max. 6ft |
| Tuning Box / Controller | 50 ft |
| Controller to External SPS | 250 ft with WG EA-Type 2 cable |

Power Preparations:

110 V (min. 3x2.5 mm²) Fuse 16 A min.. on dedicated circuit, at the same phase (L1 recommended) for all systems and deactivators at the cash desks. Current consumption max. 50 W per system, and 10/120 W (continuous / peak-pulse) per deactivator. Terminal connection or untwistable sockets. Plastic conduits (30 or 32mm)with inserted pull wire are recommended.

External alarm connection 2 conductor alarm cable or CAT 5/6 cable can be used.

Product Codes:

| | | | | |
|----|----------|-------|-------------------------------|------------|
| WG | WFFG | Floor | Guard | Antenna* |
| WG | WFCB | Floor | Guard | Controller |
| WG | WFFG2A6 | 6ft | Floor Guard antenna coil set* | |
| WG | WFFG2A10 | 10ft | Floor Guard antenna coil set* | |
| WG | WFFG2A12 | 12ft | Floor Guard antenna coil set* | |

*includes adapter box dedicated for this configuration.