



Securing Today for a Profitable Tomorrow

# Fast Pad II™

## 58KHz Distance Deactivator



The Fast Pad II Distance Deactivator provides excellent deactivation reliability and high throughput. In addition it presents a friendly man-machine interface for ease of use. The Fast Pad Antenna is configured for table-top operation but can also be set flush mount to the counter-top in a mounting tray.

Tuning is easily accomplished via the handheld IR remote, providing complete control with password protection.

**Compatible with all 58KHz Acousto-Magnetic Labels**

High Throughput With Excellent Performance and Fully Tunable

### Proximity Deactivation

With up to 10cm distance deactivation, Fast Pad is an excellent product for both source and re-tailer tagged merchandise.

### Compact Size

The small antenna footprint allows it to be easily placed on the counter top or flushmounted.

### Audible/Visual Notification

Fast Pad includes both audible and visual notification for efficient and reliable operation.

### IR Remote Controller

Fast Pad is easily tuned with a convenient hand held IR remote controller.

### LAN Port for Remote Access

With the optional EAS Net software package, Fast Pad can be remotely accessed for tuning and data mining.

### Password Protected

Individual product security is facilitated with a changeable password.

### Transmitter

Operating Frequency: 58KHz  
Transmit Burst Duration: 1.68ms  
Current: 3A Peak (Nominal)

### Regulatory

CE, FCC, UL

### Physical

Antenna: (LxWxD) 295x280x45mm  
(11.6"x11"x1.5")  
Weight: 8.5 kg (19lb)  
Control Box: (LxWxD) 275x190x125mm  
(10.8"x7.48"x4.9")  
Weight: 2.3 kg (5lb)

### Electrical

Voltage: 100/120vac, 60Hz  
220/240vac, 50Hz  
Current Draw: 6A max @240vac

### Environmental

Operating Temperature: 0-49°C (32-120°F)  
Relative Humidity: 90% Non-condensing

SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE